

QSAN XCubeSAN Series Configuration Worksheet

Use this worksheet to collect and record information for configuring the QSAN XCubeSAN series storage system. This worksheet should be used in conjunction with the [XCubeSAN QIG \(Quick Installation Guide\)](#). Refer to the chapter 2, Prepare for Installation in the [XCubeSAN SANOS 4.0 User's Manual](#) for an installation overview and additional chapters for setting up the system. The values in grey color are examples for your configuration reference.

1. Initial Configuration	
Item	Value
System Name: The maximum length of the system name is 32 characters. Valid characters are [A~Z a~z 0~9 -_].	XCubeSAN
Admin Password: The maximum length of the password is 12 characters. Valid characters are [A~Z a~z 0~9 ~!@#\$%^&* _-+=`\ (){}[];:'"<>.,?/].	1234
NTP Server: FQDN (Fully Qualified Domain Name) or IP address of NTP (Network Time Protocol) server.	pool.ntp.org
Time Zone: Depending on your location.	(GM +08:00) Taipei
2. Management Port Setting	
Item	Value
Management Port IP Address on Controller 1: IP address, subnet mask, and gateway of the management port on controller 1.	IP: 192.168.1.234 SM: 255.255.255.0 GW: 192.168.1.254
DNS Server Address: IP address of DNS (Domain Name System) server.	8.8.8.8
Management Port IP Address on Controller 2: (optional) IP address, subnet mask, and gateway of the management port on controller 2.	IP: 192.168.1.235 SM: 255.255.255.0 GW: 192.168.1.254
3. Notification Setting	
Item	Value
Email-from Address: Email-from address to send event notification.	admin@company.com

Email-to Addresses: Email-to addresses to receive event notification	Email-to Address 1: user1@company.com Email-to Address 2: user2@company.com Email-to Address 3: user3@company.com
SMTP Server: Network name or IP address of SMTP (Simple Mail Transfer Protocol) server.	smtp.company.com
Syslog Server: (optional) FQDN or IP address of syslog server.	syslog.company.com
SNMP Trap Addresses: (optional) FQDNs or IP addresses of SNMP (Simple Network Management Protocol) trap.	SNMP Trap Address 1: snmp1.company.com SNMP Trap Address 2: snmp2.company.com SNMP Trap Address 3: snmp3.company.com

4. iSCSI Port Configuration

Item		Value		
Onboard iSCSI Port IP Addresses: IP address, subnet mask, and gateway of the iSCSI ports. <ul style="list-style-type: none"> Onboard 2 x 10GBASE-T iSCSI (RJ45) ports 		/		
Controller 1	Onboard LAN1	Onboard LAN2		
IP Address	10.10.1.1	10.10.2.1		
Subnet Mask	255.255.255.0	255.255.255.0		
Gateway	10.10.1.254	10.10.2.254		
Controller 2	Onboard LAN1	Onboard LAN2		
IP Address	10.10.3.1	10.10.4.1		
Subnet Mask	255.255.255.0	255.255.255.0		
Gateway	10.10.3.254	10.10.4.254		
Slot 1 iSCSI Port IP Addresses: (optional) IP address, subnet mask, and gateway of the iSCSI ports. <ul style="list-style-type: none"> 4-port 10GbE iSCSI Host Card (SFP+) 2-port 1GBASE-T iSCSI Host Card (RJ45) 4-port 1GBASE-T iSCSI Host Card (RJ45) 		/		
Controller 1	Slot 1 LAN1	Slot 1 LAN2	Slot 1 LAN3	Slot 1 LAN4
IP Address	10.10.11.1			

Subnet Mask	255.255.255.0			
Gateway	10.10.11.254			
Controller 2	Slot 1 LAN1	Slot 1 LAN2	Slot 1 LAN3	Slot 1 LAN4
IP Address	10.10.21.1			
Subnet Mask	255.255.255.0			
Gateway	10.10.21.254			
Slot 2 iSCSI Port IP Addresses: (optional)				
IP address, subnet mask, and gateway of the iSCSI ports.				
<ul style="list-style-type: none"> • 4-port 10GbE iSCSI Host Card (SFP+) • 2-port 1GBASE-T iSCSI Host Card (RJ45) • 4-port 1GBASE-T iSCSI Host Card (RJ45) 				
Controller 1	Slot 2 LAN1	Slot 2 LAN2	Slot 2 LAN3	Slot 2 LAN4
IP Address	10.10.31.1			
Subnet Mask	255.255.255.0			
Gateway	10.10.31.254			
Controller 2	Slot 2 LAN1	Slot 2 LAN2	Slot 2 LAN3	Slot 2 LAN4
IP Address	10.10.41.1			
Subnet Mask	255.255.255.0			
Gateway	10.10.41.254			
Entity Name:			lqn.2004-08.com.qsan	
The entity name is for a device or gateway that is accessible from the network. The maximum length of the entity name is 200 characters. Valid characters are [a~z 0~9 -.:].				
iSNS IP Address: (optional)			10.1.1.1	
IP address of iSNS (Internet Storage Name Server) server.				
CHAP Username: (optional)			chap1	
CHAP (Challenge-Handshake Authentication Protocol) username. The maximum length of the username is 223 characters. Valid characters are [A~Z a~z 0~9 ~!@#%&* _+= (){}[];:<>./].				
CHAP Password: (optional)			123456789012	
CHAP password. The length of the password is between 12 to 16 characters. Valid characters are [A~Z a~z 0~9 ~!@#%&* _+=` \(){}[];:"'<>./].				
Mutual CHAP Username: (optional)			mutualchap1	
CHAP username. The maximum length of the username is 223 characters. Valid characters are [A~Z a~z 0~9 ~!@#%&* _+= (){}[];:<>./].				

Mutual CHAP Password: (optional) CHAP password. The length of the password is between 12 to 16 characters. Valid characters are [A~Z a~z 0~9 ~!@#\$\$%^&*~_+=`\ ()\{\}\[\];'"<>,.?/].	123456789012
---	--------------

5. Fibre Channel Port Configuration

Item	Value
Slot 1 Fibre Channel: (optional) Link speed and topology of the fibre channel ports. Topology support: FC-AL, point-to-point (16Gb Fibre Channel only supports Point-to-Point topology) <ul style="list-style-type: none"> 4-port 16Gb Fibre Channel Host Card (SFP+) 2-port 16Gb Fibre Channel Host Card (SFP+) 	

Controller 1	Slot 1 FC1	Slot 1 FC2	Slot 1 FC3	Slot 1 FC4
Link Speed	Auto			
Topology	Point-to-Point			
Controller 2	Slot 1 FC1	Slot 1 FC2	Slot 1 FC3	Slot 1 FC4
Link Speed	Auto			
Topology	Point-to-Point			

6. Pool Configuration

Item	Value
Pool Type: Thick Provisioning, Thin Provisioning, or Auto Tiering (Thin Provisioning Enabled).	Auto Tiering
Pool Name: The maximum length of the pool name is 16 characters. Valid characters are [A~Z a~z 0~9 -_<>].	PL1
Disks: Disk type, disk quantity, and the capacity.	SSD: 4x 100GB SAS: 4x 600GB NL-SAS: 4x 4TB
RAID Level: RAID level 0, 1, 3, 5, 6, 0+1, 10, 30, 50, 60, and N-way mirror RAID EE level 5EE, 6EE, 50EE, and 60EE	RAID 5
Raw Capacity: Sum of disk capacity.	18.8TB (= 100GB x 4 + 600GB x 4 + 4TB x 4)
Estimate Capacity: Estimate capacity according to the RAID level.	14.1TB (= 100GB x 3 + 600GB x 3 + 4TB x 3)

7. Volume Configuration	
Item	Value
Volume Name: The maximum length of the volume name is 32 characters. Valid characters are [A~Z a~z 0~9 -_<>].	V1-PL1
Capacity: Required capacity of the volume.	8TB
Volume Type: RAID Volume or Backup Volume	RAID Volume
8. LUN Mapping Configuration	
Item	Value
Protocol: iSCSI or FCP.	iSCSI
Volume Name: Select one of created volumes.	V1-PL1
Allowed Hosts: iSCSI IQN or Fibre Channel WWNN for access control. Wildcard (*) for access by all hosts.	*
Target: iSCSI Target or Fibre Channel Target	0
LUN: Support LUN (Logical Unit Number) from 0 to 255.	LUN 0
Permission: Read-only or Read-write.	Read-write
9. SSD Cache Configuration	
Item	Value
SSD Cache Pool Name: The maximum length of the pool name is 16 characters. Valid characters are [A~Z a~z 0~9 -_<>].	SCPL1
Cache Type: Read Cache (NRAID+) or Read-write Cache (RAID 1 or NRAID 1+).	Read Cache
I/O Type: Database, File System, or Web Service.	Database
SSDs: SSD quantity and the capacity.	SSD: 2x 400GB

Raw Capacity: Sum of disk capacity.	800GB	
10. Snapshot Configuration		
Item	Value	
Volume Name: Select one of created volumes.	V1-PL1	
Snapshot Space: Reserved snapshot space for the volume.	1.6TB	
Snapshot Name: The maximum length of the snapshot name is 32 characters. Valid characters are [A~Z a~z 0~9 -_<>].	Snap-V1-PL1	
Schedule Snapshots: (optional) Define the cycle of snapshots.	Daily 00:00	
11. Local Clone Configuration		
Item	Value	
Source Volume Name: Select one of created volume for source.	V1-PL1	
Source Volume Capacity: Check the capacity of source volume.	8TB	
Target Volume Name: Select one of created volume for target.	T1-PL1	
Target Volume Capacity: Check the capacity of target volume.	8TB	
Schedule Local Clones: (optional) Define the cycle of local clones.	Daily 01:00	
12. Remote Replication Configuration		
Item	Value	
Source Volume Name: Select one of created volume for source.	V1-PL1	
Source Volume Capacity: Check the capacity of source volume.	8TB	
Source iSCSI Port: iSCSI port of source unit. It can be auto or dedicated iSCSI port.	Auto	
Target iSCSI Port IP Addresses: iSCSI port IP addresses of target unit.		
Target	Controller 1	Controller 2 (optional)

IP Address	10.10.100.1	10.10.101.1
Target CHAP Username: (optional) CHAP username. The maximum length of the username is 223 characters. Valid characters are [A~Z a~z 0~9 ~!@#%&* _+= (){}[]:;<>./].	chap2	
Target CHAP Password: (optional) CHAP password. The length of the password is between 12 to 16 characters. Valid characters are [A~Z a~z 0~9 ~!@#%\$^&* _+=`\\(){}[]:;'"<>./].	123456789012	
Target Volume Name: Select one of created volume for target.	RT1-PL1	
Target Volume Capacity: Check the capacity of target volume.	8TB	
Schedule Remote Replications: (optional) Define the cycle of remote replications.	Daily 02:00	
Traffic Shaping for Peak Hour: (optional) Limit the transfer rate at peak hour.	100MB	
Traffic Shaping for Off-peak Hour: (optional) Limit the transfer rate at off-peak hour.	500MB	
Off-peak Hour: (optional) Define the off-peak hours.	Mon. ~ Fri. PM10:00 ~ AM06:59 Sat. ~ Sun. AM00:00 ~ PM23:59	

Copyright

© Copyright 2018 QSAN Technology, Inc. All rights reserved. No part of this document may be reproduced or transmitted without written permission from QSAN Technology, Inc.

March 2018

This edition applies to QSAN XCubeSAN SANOS (SAN Operating System) 4.0. QSAN believes the information in this publication is accurate as of its publication date. The information is subject to change without notice.

Trademarks

QSAN, the QSAN logo, XCbueSAN, and QSAN.com are trademarks or registered trademarks of QSAN Technology, Inc.